

RCP20 Plug-in socket receiver

ON/OFF



The bidirectional RCP20 plug-in socket receiver is simply inserted between the socket and the device that needs to be controlled.

After programming up to 32 Easywave transmitters, the device to be controlled can be switched on and off at will. Optionally, operation is also possible via a button on the receiver.

In addition, an Easywave neo server can be programmed into the receiver in order to use the bidirectional functionalities.

Energy efficient:

The RCP20 consumes only 0.4 W in standby mode.




RCP20EN5001A01-K

Technical specifications

Coding	Easywave neo Up to 32 transmitters can be programmed. POTA
Frequency	868.30 MHz
Channels	1
Power supply	230 V AC, 50 Hz (protective contact plug)
Power consumption	0.4 W standby 0.8 W relay switched (without load)
Operating modes	ON/OFF (2-button operation) ON/OFF (1-button operation) TIMER (1 second to 30 hours adjustable) LOGIC (2-button operation) DEAD MAN
Output	1x protective contact socket (D/A/NL/S/N)
Maximum contact load	16 A / 230 V AC
Operating temperature	-10 °C to +35 °C
Dimensions (W/L/H)	71.4/71.4/75.5 mm
Color	white similar RAL 9003

Plug system



D/A/NL/S/N

Scope of delivery

- Plug-in socket receiver
- Operating manual
- Quick start guide

Models

Product number	Description
RCP20EN5001A01-K	Plug-in socket receiver, Easywave neo, 230V, 1x normally open, potential-loaded, D/A/NL/S/N, white