

RTS07 Radio time switch

UP/STOP/DOWN



The RTS07 radio time switch is battery-powered and designed to be mounted indoors. It controls Easywave receivers depending on time and brightness settings.

The time switch has four individually coded radio channels enabling it to control four devices, such as electrical roller shutters, awnings or lighting.

The brightness control function for roller shutters only works in connection with the SL01 light sensor.

It is possible to transmit the different telegrams together and thus to control all four devices at the same time (group function).



RTS07E5004-01-02K

Technical specifications

Coding	Easywave
Frequency	868.30 MHz
Channels	4
Range	typically 150 m in good free-field conditions
Power supply	1x 3V-battery, CR2032
Operating indicator	Display
Operation	see operating manual
Operating temperature	0 °C to +50 °C
Dimensions (W/L/H)	80/80/16 mm
Weight	50 g (including battery)
Color	white similar RAL 9003

Scope of delivery

- Radio time switch
- Battery
- Adhesive pad
- Operating manual

Accessories (optional)

SL01E5001-01-01K Light sensor, white



Models

Product number	Description
RTS07E5004-01-02K	Radio time switch, Easywave, 4x UP/STOP/DOWN, white